


LED不閃爍
適用電子式
變壓器


輸出功率範圍 3W~6W



LED 串並數組合

- ✓ 1W LED*2串
- ✓ 1W LED*3串
- ✓ 1W LED 2串*2並

12Vin (10V ~16V)



應用產品:

- ✓ LED MR16
- ✓ LED AR111
- ✓ 任何電源輸入12V AC/DC皆可, 輸出功率1W~6W LED燈

特點:

- 輸入電壓範圍大:DC 10 to 16V / AC 12V
- 定電流輸出
- 電源轉換效率高,達93%(max)
- 具電路短路/開路保護
- 模組尺寸小:14mm*20mm,適用大多數燈組
- 適用電子變壓器,LED不閃爍

Desc.	MR16P_350 3W	MR16P_450 5W	MR16P_500 6W	MR16P_700 6W	MR16H 3W
Input Voltage (V)	AC 12V DC 10V-16V	AC 12V DC 10V-16V	AC 12V DC 10V-16V	AC 12V DC 10V-16V	AC 12V DC 10V-16V
Input Current (mA)	400mA(Max)	500mA(Max)	800mA (Max)	800mA (Max)	400mA (Max)
Efficiency	93% (Max)	93% (Max)	93% (Max)	93% (Max)	90% (Max)
Output Voltage (V)	DC 10.8V(Max)	DC 10.8V(Max)	DC 10.8V(Max)	DC 7.2V(Max)	DC 3.2V ~ 10.8V
Output Current (mA)	350mA ±5%	450mA ±5%	500mA ±5%	700mA ±5%	350mA ±5%
Output Power (W)	3W	5W	6W	6W	3W
Operating Temperature Range	-20 ^o C ~ +85 ^o C	-20 ^o C ~ +85 ^o C	-20 ^o C ~ +85 ^o C	-20 ^o C ~ +85 ^o C	-20 ^o C ~ +85 ^o C
Dimension	14mm x 20mm	14mm x 20mm	14mm x 20mm	14mm x 20mm	14mm x 20mm



HAWYANG SEMICONDUCTOR CORP. 浩陽半導體股份有限公司

Taiwan 6F., No. 96, Minchuan Rd., Xindian, Taipei County, Taiwan Tel: 886-2-2219-0903 Fax: 886-2-2219-3189

Shenzhen Room 12B-9, Zheng Quan Building, No.5020, Bin He Avenue, Fu Tian District, Shen Zhen City Tel: (0755)89807897 Fax: (0755)82990700

E-mail: power4led@hawyang-semi.com www.hawyang-semi.com / www.power4led.com